

## FM BAND PASS FILTERS FM-BPF-...

### Technical Data:

Frequency range	87.5 – 108 MHz
Max. Input power:	
FM-BPF-3	2000W
FM-BPF-4	5000W
Impedance	50 ohm
Connectors	7/16m (Default) or any connectors by request
Number of cavities	2
Return loss	> 28 dB*, * f 0 ± 100 kHz
Isolation	> 30 dB
Insertion loss	< 0.5 dB

### Design and Construction:

Material	aluminium, brass, silver plated
Frequency range	+5 ... +45 °C
Dimentions	20x41cm, h=1.4m max
Weight	30 kg

